



Dealers Industrial Equipment

No.:

Date: 12-SEP-2016

Customer :

TECHNICAL PROPOSAL

Single-phase induction motor - Squirrel cage rotor

Product line : Single-Phase : NEMA 48 & 56 ODP - Start Capacitor

Catalog Number : .5018OS1BC56CFL

List Price : \$286

Notes:

Downloaded from <http://dealerselectric.com>

Generated for Model #.5018OS1BC56CFL

Performed by:

Checked:



Dealers Industrial Equipment

No.:

Date: 12-SEP-2016

DATA SHEET

Single-phase induction motor - Squirrel cage rotor

Customer :
Product line : Single-Phase : NEMA 48 & 56 ODP - Start Capacitor

Frame : C56
Output : 0.5 HP
Frequency : 60 Hz
Poles : 4
Full load speed : 1720 rpm
Slip : 4.44 %
Voltage : 115/208-230 V
Rated current : 7.95/3.97 A
Locked rotor current : 42.1/21.1 A
Locked rotor current (I_L/I_n) : 5.3
No-load current : 5.93/2.96 A
Full load torque : 1.51 lb.ft
Locked rotor torque : 350 %
Breakdown torque : 230 %
Design : ---
Insulation class : B
Temperature rise : 80 K
Locked rotor time : 6 s (hot)
Service factor : 1.25 (1.00 at 208V)
Duty cycle : S1
Ambient temperature : -20°C - +40°C
Altitude : 1000 m
Degree of Protection : IP21
Approximate weight : 24 lb
Moment of inertia : 0.04817 sq.ft.lb
Noise level : ---

	D.E.	N.D.E.
Bearings	6203 ZZ	6202 ZZ
Regreasing interval	---	---
Grease amount	---	---

Load	Power factor	Efficiency (%)
100%	0.63	63.2
75%	0.55	61.0
50%	0.45	54.5

Notes:
Downloaded from <http://dealerselectric.com>
Generated for Model #.5018OS1BC56CFL

Performed by

Checked




Dealers Industrial Equipment

No.:

Date: 12-SEP-2016

PERFORMANCE CURVES RELATED TO RATED OUTPUT Single-phase induction motor - Squirrel cage rotor




Customer :
 Product line : Single-Phase : NEMA 48 & 56 ODP - Start Capacitor

Frame : C56	Locked rotor current (I _L /I _n) : 5.3
Output : 0.5 HP	Duty cycle : S1
Frequency : 60 Hz	Service factor : 1.25 (1.00 at 208V)
Full load speed : 1720 rpm	Design : ---
Voltage : 115/208-230 V	Locked rotor torque : 350 %
Rated current : 7.95/3.97 A	Breakdown torque : 230 %
Insulation class : B	

Notes:
 Downloaded from <http://dealerselectric.com>
 Generated for Model #.5018OS1BC56CFL

Performed by

Checked



Notes: Downloaded from <http://dealerselectric.com>
 Generated for Model #.5018OS1BC56CFL

Performed by:

Checked:

Customer:

Single-Phase : NEMA 48 & 56 ODP - Start Capacitor

C	P	ES	S	N-W
10.551	5.709	1.102	0.187	1.874
U	R	AA	AH	Flange
0.6250	0.517	NPT 1/2"	2.063	FC-149
AJ	AK	BD	BF	BB
5.874	4.500	5.748	UNC 3/8"x16-2B	0.157

Single-phase induction motor
 Frame C56 - IP21

12-SEP-2016

